

Voltage U (V)	Current I (A)	Input (W)	Speed (RPM)	Torque (Ncm)	Output (W)	Efficiency (%)
13,20	3,00	39,6	18400	1,1	21,2	53,5
13,20	3,85	50,8	14800	2,0	31,0	61,0
13,20	4,75	62,7	12300	3,0	38,6	61,6
13,20	6,15	81,2	9720	5,0	50,9	62,7
13,20	7,45	98,3	8460	7,0	62,0	63,1
13,20	8,80	116,2	7570	9,0	71,3	61,4
13,20	9,60	126,7	7300	10,0	76,4	60,3
13,20	10,70	141,2	6580	12,0	82,7	58,5
13,20	12,70	167,6	5800	15,0	91,1	54,3
13,20	16,30	215,2	4800	20,0	100,5	46,7
13,20	21,00	277,2	4000	25,0	104,7	37,8

Quiet running motor with sleeve bearings

